

Setup guide: WHMCS setup

Jellyfin Family module **WHMCS**

[Order now](#) | [Download](#) | [FAQ](#)

1. Download the latest version of the module.

PHP 8.1

```
wget https://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Jellyfin-Family/PUQ_WHMCS-Jellyfin-Family-latest.zip
```

PHP 7.4

```
wget https://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Jellyfin-Family/php74/PUQ_WHMCS-Jellyfin-Family-latest.zip
```

All versions are available via link:

http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Jellyfin-Family/

2. Unzip the archive with the module.

```
unzip PUQ_WHMCS-Jellyfin-Family-latest.zip
```

3. Copy "puqJellyfinFamily" to "WHMCS_WEB_DIR/modules/servers/"

4. Create new server Jellyfin in WHMCS (System Settings->Products/Services->Servers)

System Settings->Servers->Add New Server

- Enter the correct **Name** and **Hostname**

Name	<input type="text" value="jellyfin [REDACTED]"/>
Hostname	<input type="text" value="jellyfin [REDACTED]"/>
IP Address	<input type="text"/>
Assigned IP Addresses (One per line)	<div></div>
Monthly Cost	<input type="text"/>
Datacenter/NOC	<input type="text"/>
Maximum No. of Accounts	<input type="text" value="200"/>
Server Status Address	<div></div> <p>To display this server on the server status page, enter the full path to the folder (required to be uploaded to each server you want to monitor) - e.g. https://www.example.com/status/</p>
Enable/Disable	<input type="checkbox"/> Check to disable this server

- In the **Server Details** section, select the "**PUQ Jellyfin Family**" module and enter the correct **username**, **password** and **access hash (API key)** for the **Jellyfin web interface**.
- To check, click the "**Test connection**" button

Module	PUQ Jellyfin Family	Test Connection
✓ Connection successful. Some values have been auto-filled.		
Username	admin	
Password	
Access Hash	5 [REDACTED]	
Secure	<input checked="" type="checkbox"/> Check to use SSL Mode for Connections	
Port	443 <input type="checkbox"/> Override with Custom Port	

5. Create a new Products/Services

System Settings->Products/Services->Create a New Product

In the **Module settings** section, select the "**PUQ Jellyfin Family**" module

Module Name

PUQ Jellyfin Family

Server Group

PUQ Jellyfin Family

License key

2CLDQ2-RKSRB1

success: 2024-05-11T16:04:28+02:00

Libraries Configuration

Use All Libraries: ☒ select all libraries together

Write down the libraries you want to make available to customers of this product.
(IMPORTANT! Start a new line for each new library)
Example:
"Movies
Beginner's Programming Course
Comedy"

IMPORTANT!
If you have a folder named "-", please enter it not as the first one or rename it.
If you don't want any folder to be accessible, type "-".

Allow playback

media: ☐

audio that requires transcoding: ☐

video that requires transcoding: ☐

video that requires conversion without re-encoding: ☐

Links

Instruction:

A link to the instruction will be reflected in the client area.

Media Accounts Configuration

Count of media accounts:

20

Available number of media accounts for creation by user

Streaming bitrate limit:

Mbps

SyncPlay access:

Allow user to create and join gro

Sync playback with other devices

Remote control: ☐ Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them)

☐ Users can download media and store it on their devices. This is not the same as a sync feature. Book libraries require this enabled to function properly.

Media downloads:

User sessions:

4

A value of 0 will disable the feature.

Failed login attempts:

before user is locked out. Setting this to -1 will disable the feature.

Username prefix:

Will be attached to the beginning of username.
Only small letters and numbers and symbol "-"

Username suffix:

Will be appended to the end of username.
Only small letters and numbers and symbol "-"

Allow Live TV access: ☐

Allow Live TV recording management: ☐

Force transcoding of remote media sources such as Live TV: ☐

Show Password:

Show button

Show service password in the client area

User Configuration

Feature access

Client Area

Switch to Advanced Mode

☐ Automatically setup the product as soon as an order is placed

☒ Automatically setup the product as soon as the first payment is received

☐ Automatically setup the product when you manually accept a pending order

☐ Do not automatically setup this product

• **License key:** A pre-purchased license key for the "PUQ Jellyfin Family" module. For the module to work correctly, the key must be active

Media Accounts Configuration

- **Count of media accounts:** Available number of media accounts for creation by user.

Libraries:

- **Use All Libraries:** Choosing all of libraries from your Jellyfin server
- **Libraries:** The libraries you want to make available to customers of this product.

(IMPORTANT! Start a new line for each new library)

Example:

"Movies

Beginner`s Programming Course

Comedy"

IMPORTANT!

If you have a folder named "-", please enter it not as the first one or rename it.

If you don't want any folder to be accessible, type "-".

User Configuration:

- **Streaming bitrate limit:** An optional per-stream bitrate limit for all out of network devices. This is useful to prevent devices from requesting a higher bitrate than your internet connection can handle. This may result in increased CPU load on your server in order to transcode videos on the fly to a lower bitrate.
- **SyncPlay access:** The SyncPlay feature enables to sync playback with other devices. Select the level of access this user has to the SyncPlay
- **Remote control:** Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them)
- **Media downloads:** Users can download media and store it on their devices. This is not the same as a sync feature. Book libraries require this enabled to function properly.
- **User sessions:** Set the maximum number of simultaneous user sessions.
A value of 0 will disable the feature.
- **Failed login attempts:** Determine how many incorrect login tries can be made before lockout occurs.
A value of zero means inheriting the default of three tries for normal users and five for administrators. Setting this to -1 will disable the feature.
- **Username prefix/Username suffix:** Necessary in order to generate a username for the service, in the format: **prefix<client_id>-<service_id>suffix**

Allow playback (Restricting access to transcoding may cause playback failures in clients due to unsupported media formats)

- **media**
- **audio that requires transcoding**
- **video that requires transcoding**
- **video that requires conversion without re-encoding**

Feature access:

- **Allow Live TV access**
- **Allow Live TV recording management**
- **Force transcoding of remote media sources such as Live TV**

Links

- **Link to instruction:** Link to the instruction, if filled out, it will be reflected in the client area

Revision #2

Created 6 May 2024 08:24:07 by Yuliia Noha

Updated 20 May 2024 08:26:25 by Yuliia Noha