

Setup guide: WHMCS setup

Jellyfin module **WHMCS**

[Order now](#) | [Download](#) | [FAQ](#)

1. Download the latest version of the module.

PHP 8.1

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Jellyfin/PUQ_WHMCS-Jellyfin-latest.zip
```

PHP 7.4

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Jellyfin/php74/PUQ_WHMCS-Jellyfin-latest.zip
```

All versions are available via link:

http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Jellyfin/

2. Unzip the archive with the module.

```
unzip PUQ_WHMCS-Jellyfin-latest.zip
```

3. Copy "puqJellyfin" to "WHMCS_WEB_DIR/modules/servers/"

4. Create new server Jellyfin in WHMCS (System Settings->Products/Services->Servers)

System Settings->Servers->Add New Server

- Enter the correct **Name** and **Hostname**

Name	jellyfin [REDACTED]
Hostname	jellyfin [REDACTED]
IP Address	
Assigned IP Addresses (One per line)	
Monthly Cost	
Datacenter/NOC	
Maximum No. of Accounts	200
Server Status Address	To display this server on the server status page, enter the full path to the folder (required to be uploaded to each server you want to monitor) - e.g. https://www.example.com/status/
Enable/Disable	<input type="checkbox"/> Check to disable this server

- In the **Server Details** section, select the "**PUQ Jellyfin**" module and enter the correct **username**, **password** and **access hash (API key)** for the **Jellyfin web interface**.
- To check, click the "**Test connection**" button

Module	<div>PUQ Jellyfin</div> <div>Test Connection</div>
	✓ Connection successful. Some values have been auto-filled.
Username	<div>admin</div>
Password	<div>.....</div>
Access Hash	<div>4</div>
Secure	<input checked="" type="checkbox"/> Check to use SSL Mode for Connections
Port	<div>443</div> <div><input type="checkbox"/> Override with Custom Port</div>

Save Changes

Cancel Changes

5. Create a new Products/Services

System Settings->Products/Services->Create a New Product

In the **Module settings** section, select the "**PUQ Jellyfin**" module

License key	9T9AEM[REDACTED]2WDHP success: 2024-01-26T12:25:14+01:00	
Libraries Configuration	<p>Use All Libraries: <input type="checkbox"/> select all libraries together</p> <div> <div>Movies</div> <div>Clips</div> </div> <p>Write down the libraries you want to make available to customers of this product. (IMPORTANT! Start a new line for each new library) Example: "Movies Beginner`s Programming Course Comedy"</p> <p>IMPORTANT! If you have a folder named "-.", please enter it not as the first one or rename it. If you don't want any folder to be accessible, type "-."</p>	User Configuration
Allow playback	<p>media: <input checked="" type="checkbox"/></p> <p>audio that requires transcoding: <input checked="" type="checkbox"/></p> <p>video that requires transcoding: <input type="checkbox"/></p> <p>video that requires conversion without re-encoding: <input type="checkbox"/></p>	Feature access
Links	<p>https://doc.puq.info/books/jellyfin-whmcs-r</p> <p>Instruction: A link to the instruction will be reflected in the client area.</p>	

- **License key:** A pre-purchased license key for the **"PUQ Jellyfin"** module. For the module to work correctly, the key must be active

Libraries:

- **Use All Libraries:** Choosing all of libraries from your Jellyfin server
- **Libraries:** The libraries you want to make available to customers of this product.
(IMPORTANT! Start a new line for each new library)

Example:

"Movies

Beginner`s Programming Course

Comedy"

IMPORTANT!

If you have a folder named "-.", please enter it not as the first one or rename it.

If you don't want any folder to be accessible, type "-."

User Configuration:

- **Streaming bitrate limit:** An optional per-stream bitrate limit for all out of network devices. This is useful to prevent devices from requesting a higher bitrate than your internet connection can handle. This may result in increased CPU load on your server in order to transcode videos on the fly to a lower bitrate.
- **SyncPlay access:** The SyncPlay feature enables to sync playback with other devices. Select the level of access this user has to the SyncPlay
- **Remote control:** Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them)
- **Media downloads:** Users can download media and store it on their devices. This is not

the same as a sync feature. Book libraries require this enabled to function properly.

- **User sessions:** Set the maximum number of simultaneous user sessions.
A value of 0 will disable the feature.
- **Failed login attempts:** Determine how many incorrect login tries can be made before
lockout occurs.
A value of zero means inheriting the default of three tries for normal users and five for
administrators. Setting this to -1 will disable the feature.
- **Username prefix/Username suffix:** Necessary in order to generate a username for the
service, in the format: **prefix<client_id>-<service_id>suffix**

Allow playback (Restricting access to transcoding may cause playback failures in clients due to unsupported media formats)

- **media**
- **audio that requires transcoding**
- **video that requires transcoding**
- **video that requires conversion without re-encoding**

Feature access:

- **Allow Live TV access**
- **Allow Live TV recording management**
- **Force transcoding of remote media sources such as Live TV**

Links

- **Link to instruction:** Link to the instruction, if filled out, it will be reflected in the client
area

Revision #10

Created 2 November 2023 10:25:23 by Yuliia Noha

Updated 18 December 2023 10:56:37 by Yuliia Noha