

Add server (router Mikrotik) in WHMCS

Business-VPN module **WHMCS**

[Order now](#) | [Download](#) | [FAQ](#)

Add a new server to the system WHMCS.

Login to Your WHMCS panel and create new server in WHMCS (*System Settings->Products/Services->Servers*)

System Settings->Servers->Add New Server

[Products/Services](#)
[Configurable Products](#)
[Product Addons](#)
[Product Bundles](#)
[Domain Pricing](#)
[Domain Registrars](#)

- Enter the correct **Name** and **Hostname**
Name is just for Your convenience and You can put there anything You like ie: Mygreat mikrotik routr

You can choose whatever hostname You want. Valid entries look similar to: vpn.mydomain.com, ourgreatvpn.mydomain.net. You can also dedicate whole domain ie: myVPNservices.com if You like. The important thing is to resolve the chosen IP address of the Mikrotik router in DNS server for Your domain.

- In the "**Assigned IP Addresses field**", enter a list of IP addresses that will be issued to users.

The format in which you need to enter a list of public IP addresses and private subnets is as follows.

To define the available pool of IP addresses, for each available IP number you should enter another line where the data is separated by the "|" separator. Each line with an IP number definition has the following structure:

```
<PUBLIC_IP>|<MASK_OF_PUBLIC_NETWORK>|<PRIVATE_NETWORK>|<MASK_OF_PRIVATE_NETWORK>
```

Servers

Edit Server

Name	vpn-test.puq.pl-B
Hostname	vpn-test.puq.pl
IP Address	
Assigned IP Addresses (One per line)	77.87.125.205 25 172.16.205.0 25 77.87.125.206 25 172.16.206.0 25 77.87.125.207 25 172.16.207.0 25 77.87.125.208 25 172.16.208.0 25 77.87.125.209 25 172.16.209.0 25
Monthly Cost	0.00
Datacenter/NOC	
Maximum No. of Accounts	200
Server Status Address	<div></div> <div>To display this server on the server status page, enter the full path to the server status folder (required to be uploaded to each server you want to monitor) - eg. https://www.example.com/status/</div>
Enable/Disable	<input type="checkbox"/> Tick to disable this server

Enter the correct data in the username and password field

- In the **Server Details** section, select the "**PUQ Business-VPN**" module and enter the correct **username** and **password** for the **Mikrotik**.
- To check, click the "**Test connection**" button

Server Details

Module	<div>PUQ Business-VPN ▾</div> <div>Test Connection</div> <div>✓ Connection successful. Some values have been auto-filled.</div>
Username	<div>admin</div>
Password	<div>.....</div>
Access Hash	<div></div>
Secure	<div><input checked="" type="checkbox"/> Tick to use SSL Mode for Connections</div>
Port	<div><div>443</div><div><input type="checkbox"/> Override with Custom Port</div></div>

Revision #8
Created 18 October 2022 09:11:28 by Ruslan
Updated 11 June 2024 09:46:45 by Yuliia Noha