

Setup guide: WHMCS setup

Digital Product module **WHMCS**

[Order now](#) | [Download](#) | [FAQ](#)

Module is coded ionCube v13

Supported php version:

- php 7.4 WHMCS 8.11.0 -
- php 8.1 WHMCS 8.11.0 +
- php 8.2 WHMCS 8.11.0 +

To install and update a module, you must perform one and the same action.

1. Download the latest version of the module.

PHP 8.2

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Digital-Product/php82/PUQ_WHMCS-Digital-Product-latest.zip
```

PHP 8.1

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Digital-Product/php81/PUQ_WHMCS-Digital-Product-latest.zip
```

PHP 7.4

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Digital-Product/php74/PUQ_WHMCS-Digital-Product-latest.zip
```

All versions are available via link:

http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Digital-Product

2. Unzip the archive with the module.

```
unzip PUQ_WHMCS-Digital-Product-latest.zip
```

3. Copy and Replace "puqDigitalProduct" to "WHMCS_WEB_DIR/modules/servers/"

4. Create new server Nextcloud in WHMCS (System Settings->Products/Services->Servers)

System Settings->Servers->Add New Server

- Enter the correct **Name** and **Hostname**

Name	nextcloud- [REDACTED] com
Hostname	nextcloud- [REDACTED] com
IP Address	
Assigned IP Addresses (One per line)	
Monthly Cost	0.00
Datacenter/NOC	
Maximum No. of Accounts	200
Server Status Address	<div></div> To display this server on the server status page, enter the full path to the server status folder (required to be uploaded to each server you want to monitor) - eg. https://www.example.com/status/
Enable/Disable	<input type="checkbox"/> Tick to disable this server

- In the **Server Details** section, select the "**PUQ Digital Product**" module and enter the correct **username** and **password** for the **Nextcloud web interface**.
- To check, click the "**Test connection**" button

Server Details

Module

PUQ Digital Product

Test Connection

✓ Connection successful. Some values have been auto-filled.

Username

DigitalProduct

Password

.....

Access Hash

Secure

☒ Check to use SSL Mode for Connections

Port

443

☐ Override with Custom Port

Save Changes

Cancel Changes

5. Create a new Products/Services

System Settings->Products/Services->Create a New Product

In the **Module settings** section, select the **"PUQ Digital Product"** module

Edit Product

Details

Pricing

Module Settings

Custom Fields

Configurable Options

Upgrades

Free Domain

Cross-sells

Other

Links

Module Name

PUQ Digital Product

Server Group

None

License key

8WYEW8- -TBHURV

Success: 2024-07-08T21:14:56+02:00

Share Rescue

Digital Product 1

Select Nextcloud Resource

Password protect

YES

Password protect Nextcloud share

Prefix

whmcs-dev

Will be attached to the label of Nextcloud share.

Nextcloud share label: <PREFIX>-<CLIENT_ID>-<SERVICE_ID>

Link to instruction

https://puqcloud.com/

A link to the instruction will be reflected in the client area.

- **License key:** A pre-purchased license key for the **"PUQ Digital Product"** module. For the module to work correctly, the key must be active
- **Share Rescue:** Select the folder on the Nextcloud server that you offer as a Digital Product for downloading by the client after payment
- **Password protect:** If you want to protect the client's individual share with a password then select YES
- **Prefix:** The prefix is required to identify the client's shared link. An entry with the structure <PREFIX>-<CLIENT_ID>-<SERVICE_ID> will be added to the description of the

shared link on the nextcloud server to facilitate searching if necessary

- **Link to instruction:** Link to the instruction, if filled out, it will be reflected in the client area

Revision #7

Created 10 June 2024 02:41:55 by Ruslan

Updated 23 September 2024 21:03:09 by Ruslan