

Setup guide: WHMCS setup

Emby Family module **WHMCS**

[Order now](#) | [Download](#) | [FAQ](#)

1. Download the latest version of the module.

PHP 8.1

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Emby-Family/PUQ_WHMCS-Emby-Family-latest.zip
```

PHP 7.4

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Emby-Family/php74/PUQ_WHMCS-Emby-Family-latest.zip
```

All versions are available via link:

http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Emby-Family/

2. Unzip the archive with the module.

```
unzip PUQ_WHMCS-Emby-Family-latest.zip
```

3. Copy "puqEmbyFamily" to "WHMCS_WEB_DIR/modules/servers/"

4. Create new server Emby in WHMCS (System Settings->Products/Services->Servers)

```
System Settings->Servers->Add New Server
```

- Enter the correct **Name** and **Hostname**

Edit Server

| | |
|---|--|
| Name | en[REDACTED].pl |
| Hostname | en[REDACTED].pl |
| IP Address | |
| Assigned IP Addresses (One per line) | |
| Monthly Cost | 0.00 |
| Datacenter/NOC | |
| Maximum No. of Accounts | 200 |
| Server Status Address | To display this server on the server status page, enter the full path to the server status folder (required to be uploaded to each server you want to monitor) - eg. https://www.example.com/status/ |
| Enable/Disable | <input type="checkbox"/> Check to disable this server |

- In the **Server Details** section, select the "**PUQ Emby Family**" module and enter the correct **username**, **password** and **access hash (API key)** for the **Emby web interface**.
- To check, click the "**Test connection**" button

| | | |
|-------------|---|--|
| Module | PUQ Emby Family | <input type="button" value="Test Connection"/> |
| Username | admin | |
| Password | | |
| Access Hash | 4a[REDACTED]03 | |
| Secure | <input checked="" type="checkbox"/> Check to use SSL Mode for Connections | |
| Port | 443 | <input type="checkbox"/> Override with Custom Port |

5. Create a new Products/Services

System Settings->Products/Services->Create a New Product

In the **Module settings** section, select the **"PUQ Emby Family"** module

| | | | |
|-------------------------|--|------------------------------|---|
| Module Name | | PUQ Emby Family | |
| Server Group | | PUQ Emby Family | |
| License key | W [REDACTED] F success: 2024-07-13T10:53:59+02:00 | Media Accounts Configuration | Count of media accounts: 11 Available number of media accounts for creation by user |
| Libraries Configuration | Use All Libraries: <input type="checkbox"/> select all libraries together | User Configuration | Streaming bitrate limit: 12 Mbps |
| | Libraries: Sport Cartoons Movies Write down the libraries you want to make available to customers of this product. (IMPORTANT! Start a new line for each new library) Example: "Movies Beginner's Programming Course Comedy" IMPORTANT! If you have a folder named "-", please enter it not as the first one or rename it. If you don't want any folder to be accessible, type "-". | | Remote control: <input checked="" type="checkbox"/> Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them) <input checked="" type="checkbox"/> Users can download media and store it on their devices. This is not the same as a sync feature. Book libraries require this enabled to function properly. |
| Allow playback | media: <input checked="" type="checkbox"/> | Feature access | Media downloads: <input checked="" type="checkbox"/> Allow subtitle downloading |
| | audio that requires transcoding: <input checked="" type="checkbox"/> | | Subtitle Downloading: <input checked="" type="checkbox"/> If allowed, and if enabled in Emby mobile apps, users can automatically upload photos and videos taken from their camera to this Emby Server |
| Links | Instruction: https://doc.puq.info/books/emby-whmcs A link to the instruction will be reflected in the client area. | Client Area | Camera upload: <input checked="" type="checkbox"/> Grant or deny access to the convert media feature. |
| | | | Media conversion: <input checked="" type="checkbox"/> Only web pages containing media information are shared. Media files are never shared publicly. Shares are time-limited and will expire after 30 days. |
| | | | Social media sharing: <input checked="" type="checkbox"/> Allow this user to change their password and profile image |
| | | | User Preference Access: em1- |
| | | | Username prefix: Will be attached to the beginning of username. Only small letters and numbers and symbol "-" |
| | | | Username suffix: Will be appended to the end of username. Only small letters and numbers and symbol "-" |
| | | | Allow Live TV access: <input checked="" type="checkbox"/> |
| | | | Allow Live TV recording management: <input checked="" type="checkbox"/> |
| | | | Force transcoding of remote media sources such as Live TV: <input checked="" type="checkbox"/> |
| | | | Show Password: Show button |

Switch to Advanced Mode

- Automatically setup the product as soon as an order is placed
- Automatically setup the product as soon as the first payment is received
- Automatically setup the product when you manually accept a pending order
- Do not automatically setup this product

- **License key:** A pre-purchased license key for the "**PUQ Emby Family**" module. For the module to work correctly, the key must be active

Media Accounts Configuration

- **Count of media accounts:** Available number of media accounts for creation by user.

Libraries:

- **Use All Libraries:** Choosing all of libraries from your Jellyfin server
- **Libraries:** The libraries you want to make available to customers of this product.
(IMPORTANT! Start a new line for each new library)

Example:

"Movies

Beginner`s Programming Course

Comedy"

IMPORTANT!

If you have a folder named "-", please enter it not as the first one or rename it.

If you don't want any folder to be accessible, type "-".

User Configuration:

- **Streaming bitrate limit:** An optional per-stream bitrate limit for all out of network devices. This is useful to prevent devices from requesting a higher bitrate than your internet connection can handle. This may result in increased CPU load on your server in order to transcode videos on the fly to a lower bitrate.
- **Remote control:** Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them)
- **Media downloads:** Users can download media and store it on their devices. This is not the same as a sync feature. Book libraries require this enabled to function properly.
- **Subtitle Downloading:** Allow subtitle downloading
- **Camera upload:** If allowed, and if enabled in Emby mobile apps, users can automatically upload photos and videos taken from their camera to this Emby Server
- **Media conversion:** Grant or deny access to the convert media feature.
- **Social media sharing:** Only web pages containing media information are shared. Media files are never shared publicly. Shares are time-limited and will expire after 30 days.
- **User Preference Access:** Allow this user to change their password and profile image
- **Username prefix/Username suffix:** Necessary in order to generate a username for the service, in the format: **prefix<client_id>-<service_id>suffix**

Allow playback (Restricting access to transcoding may cause playback failures in clients due to unsupported media formats)

- **media**
- **audio that requires transcoding**

- **video that requires transcoding**
- **video that requires conversion without re-encoding**

Feature access:

- **Allow Live TV access**
- **Allow Live TV recording management**
- **Force transcoding of remote media sources such as Live TV**

Links

- **Link to instruction:** Link to the instruction, if filled out, it will be reflected in the client area

Client Area

- **Client Area:** Client zone settings, show or not show the password in the client zone, type how to show the password.

Revision #5

Created 29 April 2024 06:58:16 by Yuliia Noha

Updated 12 July 2024 05:44:45 by Yuliia Noha