

# Setup guide: WHMCS setup

## Emby Family module **WHMCS**

[Order now](#) | [Download](#) | [FAQ](#)

### 1. Download the latest version of the module.

PHP 8.1

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Emby-Family/PUQ_WHMCS-Emby-Family-latest.zip
```

PHP 7.4

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Emby-Family/php74/PUQ_WHMCS-Emby-Family-latest.zip
```

All versions are available via link:

[http://download.puqcloud.com/WHMCS/servers/PUQ\\_WHMCS-Emby-Family/](http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Emby-Family/)

### 2. Unzip the archive with the module.

```
unzip PUQ_WHMCS-Emby-Family-latest.zip
```

### 3. Copy "puqEmbyFamily" to "WHMCS\_WEB\_DIR/modules/servers/"

### 4. Create new server Emby in WHMCS (System Settings->Products/Services->Servers)

System Settings->Servers->Add New Server

- Enter the correct **Name** and **Hostname**

#### Edit Server

Name	em[REDACTED].pl
Hostname	em[REDACTED].pl
IP Address	
Assigned IP Addresses (One per line)	
Monthly Cost	0.00
Datacenter/NOC	
Maximum No. of Accounts	200
Server Status Address	To display this server on the server status page, enter the full path to the server status folder (required to be uploaded to each server you want to monitor) - eg. https://www.example.com/status/
Enable/Disable	<input type="checkbox"/> Check to disable this server

- In the **Server Details** section, select the "**PUQ Emby Family**" module and enter the correct **username**, **password** and **access hash (API key)** for the **Emby web interface**.
- To check, click the "**Test connection**" button

Module	PUQ Emby Family	<input type="button" value="Test Connection"/>
Username	admin	
Password	.....	
Access Hash	4a[REDACTED]03	
Secure	<input checked="" type="checkbox"/> Check to use SSL Mode for Connections	
Port	443 <input type="checkbox"/> Override with Custom Port	

Save Changes

Cancel Changes

## 5. Create a new Products/Services

System Settings->Products/Services->Create a New Product

In the **Module settings** section, select the **"PUQ Emby Family"** module

Module NamePUQ Emby Family

Server GroupPUQ Emby Family

License key

W F  
success: 2024-07-13T10:53:59+02:00

Media Accounts Configuration

Count of media accounts: 11  
Available number of media accounts for creation by user

Streaming bitrate limit: 12  
Mbps

Remote control:  
☒ Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them)

Media downloads:  
☒ Users can download media and store it on their devices. This is not the same as a sync feature. Book libraries require this enabled to function properly.

Subtitle Downloading:  
☒ Allow subtitle downloading

Camera upload:  
☒ If allowed, and if enabled in Emby mobile apps, users can automatically upload photos and videos taken from their camera to this Emby Server

Media conversion:  
☒ Grant or deny access to the convert media feature.

Social media sharing:  
☒ Only web pages containing media information are shared. Media files are never shared publicly. Shares are time-limited and will expire after 30 days.

User Preference Access:  
☒ Allow this user to change their password and profile image

Username prefix:  
em1-

Username suffix:  
-by1

Allow Live TV access:  
☒

Allow Live TV recording management:  
☒

Force transcoding of remote media sources such as Live TV:  
☒

Libraries Configuration

Use All Libraries: ☐ select all libraries together

Sport  
Cartoons  
Movies

Libraries:  
Write down the libraries you want to make available to customers of this product.  
**(IMPORTANT! Start a new line for each new library)**  
Example:  
"Movies  
Beginner's Programming Course  
Comedy"

**IMPORTANT!**  
If you have a folder named "-", please enter it not as the first one or rename it.  
If you don't want any folder to be accessible, type "-".

User Configuration

Media conversion:  
☒ Grant or deny access to the convert media feature.

Social media sharing:  
☒ Only web pages containing media information are shared. Media files are never shared publicly. Shares are time-limited and will expire after 30 days.

User Preference Access:  
☒ Allow this user to change their password and profile image

Username prefix:  
em1-

Username suffix:  
-by1

Allow playback

media:  
audio that requires transcoding:  
video that requires transcoding:  
video that requires conversion without re-encoding:

Feature access

media:  
audio that requires transcoding:  
video that requires transcoding:  
video that requires conversion without re-encoding:

Links

Instruction:  
https://doc.puq.info/books/emby-whmcs  
A link to the instruction will be reflected in the client area.

Client Area

Show Password:  
Show button  
Show service password in the client area

Switch to Advanced Mode

☐ Automatically setup the product as soon as an order is placed

☒ Automatically setup the product as soon as the first payment is received

☐ Automatically setup the product when you manually accept a pending order

☐ Do not automatically setup this product

- **License key:** A pre-purchased license key for the "**PUQ Emby Family**" module. For the module to work correctly, the key must be active

## Media Accounts Configuration

- **Count of media accounts:** Available number of media accounts for creation by user.

## Libraries:

- **Use All Libraries:** Choosing all of libraries from your Jellyfin server
- **Libraries:** The libraries you want to make available to customers of this product.  
**(IMPORTANT! Start a new line for each new library)**

Example:

"Movies

Beginner`s Programming Course

Comedy"

### **IMPORTANT!**

If you have a folder named "-", please enter it not as the first one or rename it.

If you don't want any folder to be accessible, type "-".

## User Configuration:

- **Streaming bitrate limit:** An optional per-stream bitrate limit for all out of network devices. This is useful to prevent devices from requesting a higher bitrate than your internet connection can handle. This may result in increased CPU load on your server in order to transcode videos on the fly to a lower bitrate.
- **Remote control:** Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them)
- **Media downloads:** Users can download media and store it on their devices. This is not the same as a sync feature. Book libraries require this enabled to function properly.
- **Subtitle Downloading:** Allow subtitle downloading
- **Camera upload:** If allowed, and if enabled in Emby mobile apps, users can automatically upload photos and videos taken from their camera to this Emby Server
- **Media conversion:** Grant or deny access to the convert media feature.
- **Social media sharing:** Only web pages containing media information are shared. Media files are never shared publicly. Shares are time-limited and will expire after 30 days.
- **User Preference Access:** Allow this user to change their password and profile image
- **Username prefix/Username suffix:** Necessary in order to generate a username for the service, in the format: **prefix<client\_id>-<service\_id>suffix**

Allow playback (Restricting access to transcoding may cause playback failures in clients due to unsupported media formats)

- **media**
- **audio that requires transcoding**

- **video that requires transcoding**
- **video that requires conversion without re-encoding**

## Feature access:

- **Allow Live TV access**
- **Allow Live TV recording management**
- **Force transcoding of remote media sources such as Live TV**

## Links

- **Link to instruction:** Link to the instruction, if filled out, it will be reflected in the client area

## Client Area

- **Client Area:** Client zone settings, show or not show the password in the client zone, type how to show the password.

---

Revision #5

Created 29 April 2024 13:58:16 by Yuliia Noha

Updated 12 July 2024 12:44:45 by Yuliia Noha