

Setup guide: WHMCS setup

Emby Family module **WHMCS**

[Order now](#) | [Download](#) | [FAQ](#)

1. Download the latest version of the module.

PHP 8.1

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Emby-Family/PUQ_WHMCS-Emby-Family-latest.zip
```

PHP 7.4

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Emby-Family/php74/PUQ_WHMCS-Emby-Family-latest.zip
```

All versions are available via link:

http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-Emby-Family/

2. Unzip the archive with the module.

```
unzip PUQ_WHMCS-Emby-Family-latest.zip
```

3. Copy "puqEmbyFamily" to "WHMCS_WEB_DIR/modules/servers/"

4. Create new server Emby in WHMCS (System Settings->Products/Services->Servers)

```
System Settings->Servers->Add New Server
```

- Enter the correct **Name** and **Hostname**

Edit Server

Name	en[REDACTED].pl
Hostname	en[REDACTED].pl
IP Address	
Assigned IP Addresses (One per line)	
Monthly Cost	0.00
Datacenter/NOC	
Maximum No. of Accounts	200
Server Status Address	To display this server on the server status page, enter the full path to the server status folder (required to be uploaded to each server you want to monitor) - eg. https://www.example.com/status/
Enable/Disable	<input type="checkbox"/> Check to disable this server

- In the **Server Details** section, select the **"PUQ Emby Family"** module and enter the correct **username**, **password** and **access hash (API key)** for the **Emby web interface**.
- To check, click the **"Test connection"** button

Module	PUQ Emby Family	<input type="button" value="Test Connection"/>
Username	admin	
Password	
Access Hash	4a[REDACTED]03	
Secure	<input checked="" type="checkbox"/> Check to use SSL Mode for Connections	
Port	443	<input type="checkbox"/> Override with Custom Port

5. Create a new Products/Services

System Settings->Products/Services->Create a New Product

In the **Module settings** section, select the **"PUQ Emby Family"** module

Module Name		PUQ Emby Family	
Server Group		PUQ Emby Family	
License key	W [REDACTED] F success: 2024-07-13T10:53:59+02:00	Media Accounts Configuration	Count of media accounts: 11 Available number of media accounts for creation by user
Libraries Configuration	Use All Libraries: <input type="checkbox"/> select all libraries together	User Configuration	Streaming bitrate limit: 12 Mbps
	Libraries: Sport Cartoons Movies Write down the libraries you want to make available to customers of this product. (IMPORTANT! Start a new line for each new library) Example: "Movies Beginner's Programming Course Comedy" IMPORTANT! If you have a folder named "-", please enter it not as the first one or rename it. If you don't want any folder to be accessible, type "-".		Remote control: <input checked="" type="checkbox"/> Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them) <input checked="" type="checkbox"/> Users can download media and store it on their devices. This is not the same as a sync feature. Book libraries require this enabled to function properly.
Allow playback	media: <input checked="" type="checkbox"/>	Feature access	Media downloads: <input checked="" type="checkbox"/> Allow subtitle downloading
	audio that requires transcoding: <input checked="" type="checkbox"/>		Subtitle Downloading: <input checked="" type="checkbox"/> If allowed, and if enabled in Emby mobile apps, users can automatically upload photos and videos taken from their camera to this Emby Server
Links	Instruction: https://doc.puq.info/books/emby-whmcs A link to the instruction will be reflected in the client area.	Client Area	Camera upload: <input checked="" type="checkbox"/> Grant or deny access to the convert media feature.
			Media conversion: <input checked="" type="checkbox"/> Only web pages containing media information are shared. Media files are never shared publicly. Shares are time-limited and will expire after 30 days.
			Social media sharing: <input checked="" type="checkbox"/> Allow this user to change their password and profile image
			User Preference Access: em1-
			Username prefix: Will be attached to the beginning of username. Only small letters and numbers and symbol "-"
			Username suffix: Will be appended to the end of username. Only small letters and numbers and symbol "-"
			Allow Live TV access: <input checked="" type="checkbox"/>
			Allow Live TV recording management: <input checked="" type="checkbox"/>
			Force transcoding of remote media sources such as Live TV: <input checked="" type="checkbox"/>
			Show Password: Show button

Switch to Advanced Mode

- Automatically setup the product as soon as an order is placed
- Automatically setup the product as soon as the first payment is received
- Automatically setup the product when you manually accept a pending order
- Do not automatically setup this product

- **License key:** A pre-purchased license key for the "**PUQ Emby Family**" module. For the module to work correctly, the key must be active

Media Accounts Configuration

- **Count of media accounts:** Available number of media accounts for creation by user.

Libraries:

- **Use All Libraries:** Choosing all of libraries from your Jellyfin server
- **Libraries:** The libraries you want to make available to customers of this product.
(IMPORTANT! Start a new line for each new library)

Example:

"Movies

Beginner`s Programming Course

Comedy"

IMPORTANT!

If you have a folder named "-", please enter it not as the first one or rename it.

If you don't want any folder to be accessible, type "-".

User Configuration:

- **Streaming bitrate limit:** An optional per-stream bitrate limit for all out of network devices. This is useful to prevent devices from requesting a higher bitrate than your internet connection can handle. This may result in increased CPU load on your server in order to transcode videos on the fly to a lower bitrate.
- **Remote control:** Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them)
- **Media downloads:** Users can download media and store it on their devices. This is not the same as a sync feature. Book libraries require this enabled to function properly.
- **Subtitle Downloading:** Allow subtitle downloading
- **Camera upload:** If allowed, and if enabled in Emby mobile apps, users can automatically upload photos and videos taken from their camera to this Emby Server
- **Media conversion:** Grant or deny access to the convert media feature.
- **Social media sharing:** Only web pages containing media information are shared. Media files are never shared publicly. Shares are time-limited and will expire after 30 days.
- **User Preference Access:** Allow this user to change their password and profile image
- **Username prefix/Username suffix:** Necessary in order to generate a username for the service, in the format: **prefix<client_id>-<service_id>suffix**

Allow playback (Restricting access to transcoding may cause playback failures in clients due to unsupported media formats)

- **media**
- **audio that requires transcoding**

- **video that requires transcoding**
- **video that requires conversion without re-encoding**

Feature access:

- **Allow Live TV access**
- **Allow Live TV recording management**
- **Force transcoding of remote media sources such as Live TV**

Links

- **Link to instruction:** Link to the instruction, if filled out, it will be reflected in the client area

Client Area

- **Client Area:** Client zone settings, show or not show the password in the client zone, type how to show the password.

Revision #5

Created 29 April 2024 13:58:16 by Yuliia Noha

Updated 12 July 2024 12:44:45 by Yuliia Noha