

# Product Configuration

Jellyfin module **WHMCS**

[Order now](#) | [Download](#) | [FAQ](#)

Create a new Products/Services

System Settings->Products/Services->Create a New Product

In the **Module settings** section, select the "**PUQ Jellyfin**" module

Details
 Pricing 
 Module Settings 
 Custom Fields 
 Configurable Options 
 Upgrades 
 Free Domain 
 Cross-sells 
 Other 
 Links

Module Name:

Server Group:

---

License key:   
success: 2026-04-15T11:59:03+02:00

**Libraries Configuration**

Use All Libraries:  select all libraries together

Playlists

Movies

Write down the libraries you want to make available to customers of this product.  
**(IMPORTANT! Start a new line for each new library)**  
 Example:  
 "Movies  
 Beginner's Programming Course  
 Comedy"

**IMPORTANT!**  
 If you have a folder named "-", please enter it not as the first one or rename it. If you don't want any folder to be accessible, type "-".

media:

audio that requires transcoding:

video that requires transcoding:

video that requires conversion without re-encoding:

---

**Links**

Instruction:   
A link to the instruction will be reflected in the client area.

**User Configuration**

Streaming bitrate limit:   
Mbps. Please provide number from 1 to 60

SyncPlay access:   
Sync playback with other devices

Remote control:  Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them)

Media downloads:  Users can download media and store it on their devices. This is not the same as a sync feature. Book libraries require this enabled to function properly.

User sessions:  A  
value of 0 will disable the feature.

Failed login attempts:   
before user is locked out. Setting this to -1 will disable the feature.

Username prefix:   
Will be attached to the beginning of username. Only small letters and numbers and symbol "-"

Username suffix:   
Will be appended to the end of username. Only small letters and numbers and symbol "-"

---

Allow Live TV access:

Allow Live TV recording management:

Force transcoding of remote media sources such as Live TV:

---

**Client Area**

Show Password:   
Show service password in the client area

Password Generation:   
Set the password length and the allowed letters/numbers/symbols for the password. Format: "8:234abcdABCD", where 8 is the password length, and everything after the colon represents the allowed characters.

Username Format:   
{user\_id}-{random\_letter\_7}

Custom Username:   
Unix time: {unixtime} Year: {year}, Month: {month}, Day: {day}, Hour: {hour}, Minute: {minute}, Second: {second}

Automatically setup the product as soon as an order is placed

Automatically setup the product as soon as the first payment is received

Automatically setup the product when you manually accept a pending order

Do not automatically setup this product

- **License key:** A pre-purchased license key for the "PUQ Jellyfin" module. For the module to work correctly, the key must be active

## Libraries:

- **Use All Libraries:** Choosing all of libraries from your Jellyfin server
- **Libraries:** The libraries you want to make available to customers of this product.  
**(IMPORTANT! Start a new line for each new library)**

Example:

"Movies

Beginner`s Programming Course

Comedy"

**IMPORTANT!**

If you have a folder named "-", please enter it not as the first one or rename it.  
If you don't want any folder to be accessible, type "-".

## User Configuration:

- **Streaming bitrate limit:** An optional per-stream bitrate limit for all out of network devices. This is useful to prevent devices from requesting a higher bitrate than your internet connection can handle. This may result in increased CPU load on your server in order to transcode videos on the fly to a lower bitrate.
- **SyncPlay access:** The SyncPlay feature enables to sync playback with other devices. Select the level of access this user has to the SyncPlay
- **Remote control:** Remote control of shared devices (DLNA devices are considered shared until a user begins controlling them)
- **Media downloads:** Users can download media and store it on their devices. This is not the same as a sync feature. Book libraries require this enabled to function properly.
- **User sessions:** Set the maximum number of simultaneous user sessions. A value of 0 will disable the feature.
- **Failed login attempts:** Determine how many incorrect login tries can be made before lockout occurs. A value of zero means inheriting the default of three tries for normal users and five for administrators. Setting this to -1 will disable the feature.
- **Username prefix/Username suffix:** Necessary in order to generate a username for the service, in the format: **prefix<client\_id>-<service\_id>suffix**

Allow playback (Restricting access to transcoding may cause playback failures in clients due to unsupported media formats)

- **media**
- **audio that requires transcoding**
- **video that requires transcoding**
- **video that requires conversion without re-encoding**

## Feature access:

- **Allow Live TV access**
- **Allow Live TV recording management**
- **Force transcoding of remote media sources such as Live TV**

## Links

- **Link to instruction:** Link to the instruction, if filled out, it will be reflected in the client area

## Client Area

- **Show Password** - Show the service password in the client area.
- **Password Generation** - Set the password length and the allowed

letters/numbers/symbols for the password.

Format: `"8: 234abcdABCD"`, where `8` is the password length, and everything after the colon represents the allowed characters.

- **Username Format** – Define the format for username generation:
    - **Standard** – prefix-client\_id-service\_id-suffix
    - **Custom** – username generated by a custom rule
  - **Custom Username** – Set a rule for generating a custom username.
- 

Revision #12

Created 2 November 2023 13:46:50 by Yuliia Noha

Updated 3 October 2025 12:24:38 by Yuliia Noha