

# Add server (Mikrotik) in WISECP

## Mikrotik WireGuard Business-VPN module

### WISECP

[Order now](#) | [Download](#) | [FAQ](#)

1. Log in to the administrative area of your **WISECP**.
2. Go to module configuration.


Services -> Service Management -> Module Settings -> Other -> All Modules -> PUQ Mikrotik WireGuard Business-VPN

The screenshot displays the WISECP administrative dashboard. At the top, there is a navigation bar with the WISECP logo and a search bar. Below the navigation bar, there are several menu items: Settings, Orders (5), Billing, Clients, Tools, WAnalytics, Support, Services, Site Management, Languages, and Help. The 'Services' menu is currently selected, and a dropdown menu is visible, showing options like Service Management, Hosting Management, Domain Name Registration, Software Services, Add Group, Module Settings, Addons, and Order Requirements. The 'Module Settings' option is highlighted with a red underline. In the background, there are two summary cards: 'Today Sales (Turnover)' for 'Yesterday' and 'Current Cash' for 'Current Month Expenses', both showing a value of €0.

WISECP Smart Search


Settings Orders (5) Billing Clients Tools WAnalytics Support Services Site Management Languages Help

### Module Settings




SSL Certificate

Manage



Product License

Manage



Other

Manage

WISECP Smart Search

Settings Orders (5) Billing Clients Tools WAnalytics Support Services Site Management Languages Help

## Other

Initial Settings All Modules

WISECP Smart Search

Settings Orders Billing Clients Tools WAnalytics Support Services Site Management Languages Help

## Other

Dashboard / Module Settings / C

Initial Settings All Modules

### Search Within Modules

Write something...

Search results showing a list of modules, with 'PUQ Mikrotik WireGuard VPN' highlighted.

3. In the opened page, click the '**Add Server**' button.

Other Dashboard / Module Setting

Initial Settings All Modules

PUQ Mikrotik WireGuard Business-VPN **PUQ**  
cloud

License key R1BCGH-...-YYQRKX 2023-12-20T22:17:00+01:00 Check and Save

Version: 1.0 Web Site Documentation Changelog

**+ Add New Server** Server Groups

Servers [MikroTik](#)

10 Show Record Search

#	Name	Status	Group	Default	IP/Domain	Usage Stats
2	vpn-test.uuq.pl	active	Default	✔	vpn-test.uuq.pl	1/12

Showing records from 1 to 1 - 1 Prev 1 Next

#### 4. On the opened page, enter all the necessary information:

- **Name:** Displayed name of the server.
- **Maximum Number of Accounts:** The number of services that can be on this server.
- **Server Group:** Optionally, choose the server group.
- **DNS 1 and DNS 2:** are DNS servers that will be specified in the configuration of WireGuard clients.
- **Assigned IP Addresses:** a list of Interface for public IP, Public IP, Private Net that will be assigned to WireGuard VPN clients, with each address on a new line. Format:

```
<interface>|<public_ip>/<mask>|<private_network>/<mask>
```

- **IP Address or Domain:** The address of the MikroTik router you are connecting to.
- **Username:** is the username for the account on MikroTik.
- **Password:** is the password for the account on MikroTik.
- Check the **SSL** box if you want to use SSL-encrypted connection. If necessary, specify the port and perform a connection test.

[< Go to Back](#)

## Add New Server

Name	vpn-test.uuq.pl
Maximum Number of Accounts	10
Server Group	Default <span>▼</span>
Default	<input type="checkbox"/> Set as default server in group
DNS 1	77.87.125.10
DNS 2	77.87.125.20
Assigned IP Addresses <small>(One per line)</small>	<p>ether1-pub 77.87.125.206/25 192.168.101.0/24                      ether1-pub 77.87.125.207/25 192.168.102.0/24                      ether1-pub 77.87.125.208/25 192.168.103.0/24                      ether1-pub 77.87.125.209/25 192.168.104.0/24                      ether1-pub 77.87.125.210/25 192.168.105.0/24                      ether1-pub 77.87.125.211/25 192.168.106.0/24                      ether1-pub 77.87.125.212/25 192.168.107.0/24                      ether1-pub 77.87.125.213/25 192.168.108.0/24</p> <p><small>&lt;interface&gt; &lt;public_ip&gt;/&lt;mask&gt; &lt;private_network&gt;/&lt;mask&gt;</small></p>
IP Address or Domain	vpn-test.uuq.pl
Username	wisecp-dev-MWG
Password	<input type="password"/>
SSL	<input checked="" type="checkbox"/> Connect using SSL
Port	443 <input type="checkbox"/> Change standard port
Test Connection	<input type="button" value="Test Connection"/>

[Add New Server](#)

Revision #1

Created 25 November 2023 07:55:45 by Ruslan

Updated 25 November 2023 15:44:33 by Ruslan