

Installation and configuration guide

- [1. WHMCS setup\(install/update\)](#)
- [2. PUQVPNCP installation and configuration](#)
- [3. Add server \(PUQVPNCP\) in WHMCS](#)
- [4. Product Configuration](#)
- [5. Localization change Configuration](#)
- [Email Template \(puqWireGuard Custom welcome email template\)](#)
- [Email Template \(puqWireGuard Custom change package Email template\)](#)
- [Important Information About Generating a Unique Open Link for QR Code Delivery in an Email Template](#)

1. WHMCS setup(install/update)

[Order now](#) | [Download](#) | [FAQ](#)

To install and update a module, you must perform one and the same action.

1. Download the latest version of the module.

PHP 8.1

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-WireGuard-VPN/PUQ_WHMCS-WireGuard-VPN-latest.zip
```

PHP 7.4

```
wget http://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-WireGuard-VPN/php74/PUQ_WHMCS-WireGuard-VPN-latest.zip
```

All versions are available: https://download.puqcloud.com/WHMCS/servers/PUQ_WHMCS-WireGuard-VPN/

2. Unzip the archive with the module.

```
unzip PUQ_WHMCS-WireGuard-VPN-latest.zip
```

3. Copy and Replace "puqWireGuardVPN" from "PUQ_WHMCS-WireGuard-VPN" to "WHMCS_WEB_DIR/modules/servers/"

2. PUQVPNCP installation and configuration

[Order now](#) | [Download](#) | [FAQ](#)

Official documentation:

[PUQVPNCP Documentation](#)

[PUQVPNCP Download](#)

[PUQVPNCP Order now](#)

1. Install the required packages

```
apt-get update
apt-get install wireguard wireguard-dkms wireguard-tools -y
apt-get install iproute2 iptables -y
apt-get install bind9 -y
```

2. Download the latest version of the package

<https://download.puqcloud.com/cp/puqvpncp/>

3. Install the puqvpncp package

```
wget https://download.puqcloud.com/cp/puqvpncp/puqvpncp_1.1-2_amd64.deb
dpkg -i puqvpncp_1.1-2_amd64.deb
```

4. After installation, connect to your server via a web browser.

http://SERVER_IP:8098
Username: admin

Password: admin

PUQVPNCP

? HELP ?

ruslan (79.184.10.59)

Logout

Dashboard

VPN servers

VPN accounts

Settings

About us

Server Information

Hostname: dev.softkeel.com

OS Name: Debian GNU/Linux 11 (bullseye)

Architecture: amd64

CPU: Common KVM processor

CPU Threads: 4 Load: 0.02, 0.09, 0.14

Memory: 7956 MiB Used: 70%

Timezone: Europe/Warsaw

PUQVPNCP

Status: OK

Version: 1.0

WireGuards: 109

VPN Accounts: 548/550

License: 2023-11-13T18:38:43+01:00

License

Reload

WireGuard

wireguard: 1.0.20210223-1

wireguard-dkms: 1.0.20210219-1

wireguard-tools: 1.0.20210219-1

Configure

Firewall

iptables: 1.8.7-1

iproute2: 5.10.0-4

Configure

DNS server

bind9: 1:9.16.33-1~deb11u1

Running: PID: 3092940

Configure

```
nano /etc/puqvpnnp/puqvpnnp.conf
```

```
LetsEncryptSSL=yes
```

```
Domain=XXXXXX.XXX
```

Restart the **PUQVPNCP** service

```
service puqvpnnp restart
```

After these steps, the first time you connect to the server via the https protocol, the system will request an SSL certificate and automatically renew it if necessary.

ATTENTION. After activating SSL, the system will only work in the https protocol on port 443. A redirect is also set from port 80 to port 443.

To connect to the server via the https protocol, use only the domain that was set in the configuration file. Otherwise, you will get an error that SSL is not working correctly.

6. License configuration is available in the menu item **Settings->License**

PUQVPNCP

? HELP ?

ruslan (79.184.10.59)

Logout

By default, the system limit is 50 users and the API is disabled.

In order to activate the license key, the key must be entered in the "License Key" field and click on the "Save" button

PUQVPNCP ? HELP ? ruslan (79.184.10.59) Logout

Dashboard VPN servers VPN accounts Settings About us

Settings

Firewall DNS One-time link System users API License

API Access Hashes

Successfully

Name IP Add

Everything went well. Please save the hash. It has only been shown once.

Access hash Copy hash

Name	IP	Created data	Last Login	
test2	1.1.1.1	2022-11-18T10:38:37+01:00		Delete
TEST	79.184.10.59	2022-11-15T15:23:05+01:00	2022-11-17T09:36:57+01:00	Delete
piotr2	79.184.10.59	2022-11-17T14:26:40+01:00	2022-11-17T14:42:08+01:00	Delete
Piotr	79.184.10.59	2022-11-16T14:23:48+01:00		Delete

Enter the name and IP address of the WHMCS server and click the ADD button

Attention.

The generated Access hash will only be shown once. Copy it, it will be needed during configuration of the product server in the WHMCS system.

Accept the fact that once the Access Hashs API is created, it will only be shown once. Each API Access Hash only works from a specific IP address.

8. Creation of access API

Add new WireGuard is available in the menu item **VPN servers->WireGuard->Click Create**

PUQVPNCP

? HELP ?

ruslan (79.184.7.48)

Logout

Dashboard

VPN servers

WireGuard

VPN accounts

Settings

About us

WireGuard

Create

Find By Name

Peers

Find By Interface

Find By Network

Internal Traffic

Port

External IP

DNS

Peer Download

Peer Upload

1-4819	0	wg7	10.0.6.1/24	YES	51827	77.87.125.209	8.8.8.8	1.1.1.1	3M	4M	Edit	Delete
1-4820	1	wg8	10.0.7.1/24	YES	51828	77.87.125.200	8.8.8.8	1.1.1.1	3M	4M	Edit	Delete
77_87_125_209	7	wg110	10.0.110.1/24	YES	51930	77.87.125.200	10.0.110.1		12M	12M	Edit	Delete

PUQVPNCP

? HELP ?

ruslan (79.184.7.48)

Logout

Dashboard

VPN servers

VPN accounts

Settings

About us

WireGuard / Add WireGuard

Add

Name

Default_7

Private key

WE+qTOu2TvtwKtuMs5hjecxO2zFXqC

Public key

O1f/+xedMQqJj+cRE+DOfk6wDawH5J

Interface name

wg24

IP/MASK

10.0.22.1/24

Internal Traffic

DROP

Port

51844

External IP

77.87.125.200

DNS 1

10.0.22.1

DNS 2

77.87.125.200

Peers configuration

Bandwidth download (in M) per peer

0

Bandwidth upload (in M) per peer

0

Enter or edit the parameters of the new server/interface and click the **ADD** button

3. Add server (PUQVPNCP) in WHMCS

[Order now](#) | [Download](#) | [FAQ](#)

Add a new server to the system WHMCS.

Login to Your WHMCS panel and create new server in WHMCS (*System Settings->Products/Services->Servers*)

System Settings->Servers->Add New Server

[Products/Services](#)
[Configure the core](#)
[Product Addons](#)
[Product Bundles](#)
[Domain Pricing](#)
[Domain Registrars](#)

• Enter the correct **Name** and **Hostname**

Name is just for Your convenience and You can put there anything You like ie:

My great PUQVPNCP routr

You can choose whatever hostname You want. Valid entries look similar to:
vpn.mydomain.com, ourgreatvpn.mydomain.net. You can also dedicate whole domain ie: myVPNservices.com if You like. The important thing is to resolve the chosen IP address of the PUQVPNCP in DNS server for Your domain.

Servers

Edit Server

Name	<input type="text" value="WireGuardVPNServer"/>
Hostname	<input type="text" value="test-puqvpncp.uuq.pl"/>
IP Address	<input type="text"/>
Assigned IP Addresses (One per line)	<div></div>
Monthly Cost	<input type="text" value="0.00"/>
Datacenter/NOC	<input type="text"/>
Maximum No. of Accounts	<input type="text" value="200"/>
Server Status Address	<div><input type="text"/> To display this server on the server status page, enter the full path to the server status folder (required to be uploaded to each server you want to monitor) - eg. https://www.example.com/status/</div>
Enable/Disable	<input type="checkbox"/> Check to disable this server

Enter the correct data in the Access Hash field

- In the **Server Details** section, select the "**PUQ WireGuard VPN**" module and enter the correct API Access Hash.
- To check, click the "**Test connection**" button

If you save the correct login and password for PUQVPNC in the server settings, then the Login to PUQ VPN Control Panel button will open for you without entering a login and password.

Server Details

Module	<div>PUQ WireGuard VPN</div> <div>Test Connection</div> <div>✓ Connection successful. Some values have been auto-filled.</div>
Username	<div></div>
Password	<div></div>
Access Hash	<div>73aed93685cae7325ad1b43a93c633ac1df6ba88326f7f578b0fb6516061c868cd03f0d7629d19eb</div>
Secure	<div><input checked="" type="checkbox"/> Check to use SSL Mode for Connections</div>
Port	<div><div>443</div><div><input type="checkbox"/> Override with Custom Port</div></div>

Save Changes

Cancel Changes

4. Product Configuration

[Order now](#) | [Download](#) | [FAQ](#)

Add new product to WHMCS

System Settings->Products/Services->Create a New Product

In the **Module settings** section, select the "**PUQ WireGuard VPN**" module

• **License key:** A pre-purchased license key for the "**PUQ WireGuard VPN**" module. For the module to work correctly, the key must be active

Server Group: UA PUQVPNC

VPN Server

License key: success: 2023-12-22T16:20:58+01:00

• Please select your server from the list. The list is loaded inconsistently from the server

Link settings

• **Link to instruction** - If you have prepared instructions for your customers on how to use the service, then a link to the instructions is provided here (If filled, it will be shown in the client area)

• **Link to VPN clients** - Link to download the VPN client. For example <https://www.wireguard.com/install/> (If filled, it will be shown in the client area)

• **Custom Welcome Email** - Drop-down list of available e-mail templates for the action of creating a new client account. Please note that it is necessary to disable the standard welcome email in order to avoid double notification

• **Custom Change localization Email** - Drop-down list of available e-mail templates for the localization change action (package change) for the client account. Please note that you need to disable the standard package change email to avoid double notification.

VPN users settings

• **Bandwidth Download** - Bandwidth Download of VPN accounts (**package change**)

• **Bandwidth Upload** - BandwidthUpload of VPN accounts (**package change**)

E-mail configuration

VPN users settings

5. Localization change Configuration

[Order now](#) | [Download](#) | [FAQ](#)

To ensure the functionality of changing localization, you need to make some settings. We will give an example of such a configuration with two independent installations where "(UA) PUQ WireGuard VPN" and "(PL) PUQ WireGuard VPN" are two different packages that have two independent groups of servers and have different locations. In our example, we simulate two localizations and the ability to change client packages, which allow changing localization, it is also worth noting that in our configuration example, many servers are used in each of the two groups, where the server is selected according to the least loaded one, which is necessary for correct load distribution between servers.

Attention! For the correct operation of this functionality, available servers are required. If the server is unavailable, changing the package when changing the locale will fail.

1. Add necessary services according to your requirements. ([How to add servers](#))

2. Add your servers to specific server groups.

PL 1	-	0/200 (0%)	Not Available	Login to PUQ VPN Control Panel	✓	🔧	⊖
Add your servers for the first group:							
PL 2	-	1/8 (13%)	Not Available	Login to PUQ VPN Control Panel	✓	🔧	⊖
Add your servers for the second group:							

Server groups look like this:

Note. Currently only the "Add to the least full server" scenario is implemented.

3. Select the appropriate server groups in the corresponding product.

PL PUQVPNCP	Add to the least full server	PL 1, PL 2, PL 3	🔧	⊖
Choose your servers group for the first product:				
Choose your servers group for the second product:				
<div>Module Name PUQ WireGuard VPN</div>				

4. Select the appropriate package to update.

Choose your package update for the first product:

Edit Product

Details

Pricing

Module Settings

Custom Fields

Configurable Options

Upgrades

Free Domain

Cross-sells

Other

Links

Packages Upgrades

PUQ WireGuard VPN - (PL) PUQ WireGuard VPN

Use Ctrl+Click to select multiple packages

Configurable Options

☐ Check to allow Upgrading/Downgrading of configurable options

Upgrade Email

None

Choose your package update for the second product:

Edit Product

Details

Pricing

Module Settings

Custom Fields

Configurable Options

Upgrades

Free Domain

Cross-sells

Other

Links

Packages Upgrades

PUQ WireGuard VPN - (UA) PUQ WireGuard VPN

Use Ctrl+Click to select multiple packages

Configurable Options

☐ Check to allow Upgrading/Downgrading of configurable options

Upgrade Email

None

Note. Please note that in order to avoid double notification, notification by means of WHMCS is disabled, because a custom notification will be used.

Email Template

(puqWireGuard Custom welcome email template)

[Order now](#) | [Download](#) | [FAQ](#)

Create an email template for customer notifications.

System Settings->Email Templates->Create New Email Template

- **Email Type:** Product/service

Unique Name: puqWireGuard Custom welcome email template

Subject: Create New Email Template	
Welcome to Your New VPN Service - Connection Information Enclosed	
Email Type	
Body:	Product/Service
<p>Dear {{\$client_name}},</p> <p>Congratulations and welcome to your new VPN service! We are excited to have you on board, and we appreciate your trust in us to provide you with a secure, private, and fast online experience.</p> <p>To get started, please find your VPN connection details below:</p> <p>Username: {{\$user}}</p> <p>Password: {{\$password}}</p> <p>Server Hostname: {{\$server_hostname}}</p> <p>Available connection protocols: {{\$protocol}}</p>	

One-time link where you will find all comprehensive information:

{\${otl}}

Here you will find all the information about the possibility of connecting to a VPN service. Attention! You can use this link only once, if you need to get the login data from the link again, use the client panel to generate a new link.

Android app download link: <https://play.google.com/store/apps/details?id=com.wireguard.android>

iPhone app download link: <https://apps.apple.com/us/app/wireguard/id1441195209>

To quickly connect after downloading the official WireGuard app for your device, scan the QR code below.

{\${qrcode_small}}

small size

{\${qrcode_medium}}

medium size

{\${qrcode_large}}

large size

{\${qrcode_max}}

max size

You can use these credentials to connect to our VPN service using your preferred VPN client or app. If you need assistance with setting up the connection or require a step-by-step guide, please visit our support page: [your-company-support-page-link].

For your convenience, we have also attached a detailed user manual to this email. The manual will provide you with comprehensive instructions on how to use our service and configure your VPN connection.

Please keep this email safe, as it contains sensitive information about your VPN account. We strongly advise you not to share your login credentials with anyone.

Once again, thank you for choosing our VPN service. We are committed to providing you with the best online experience, and we look forward to serving you.

{signature}

Email Template (puqWireGuard Custom change package Email template)

[Order now](#) | [Download](#) | [FAQ](#)

Create an email template for customer notifications.

System Settings->Email Templates->Create New Email Template

- **Email Type:** Product/service

Unique Name: puqWireGuard Custom change package Email template

Create New Email Template

Subject:

You have changed the location in your VPN service - connection information is attached

Product/Service

Body:

Dear {\$client_name},

You received this email because your connection location has changed.

To continue, find your VPN connection information below:

Username: {\$user}
Password: {\$password}
Server Hostname: {\$server_hostname}

Available connection protocols: {\$protocol}

One-time link where you will find all comprehensive information:

{\$otl}

Here you will find all the information about the possibility of connecting to a VPN service. Attention! You can use this link only once, if you need to get the login data from the link again, use the client panel to generate a new link.

Android app download link: <https://play.google.com/store/apps/details?id=com.wireguard.android>

iPhone app download link: <https://apps.apple.com/us/app/wireguard/id1441195209>

To quickly connect after downloading the official WireGuard app for your device, scan the QR code below.

{\$qrcode_small}

small size

{\$qrcode_medium}

medium size

{\$qrcode_large}

large size

{\$qrcode_max}

max size

You can use these credentials to connect to our VPN service using your preferred VPN client or app. If you need assistance with setting up the connection or require a step-by-step guide, please visit our support page: [your-company-support-page-link].

For your convenience, we have also attached a detailed user manual to this email. The manual will provide you with comprehensive instructions on how to use our service and configure your VPN connection.

Please keep this email safe, as it contains sensitive information about your VPN account. We strongly advise you not to share your login credentials with anyone.

Once again, thank you for choosing our VPN service. We are committed to providing you with

the best online experience, and we look forward to serving you.

{signature}

Subject: You have changed the location in your VPN service - connection information is attached

Important Information About Generating a Unique Open Link for QR Code Delivery in an Email Template

[Order now](#) | [Download](#) | [FAQ](#)

Introduction

This process allows for the generation of unique open links for QR codes that can be incorporated into email templates in WHMCS. This is convenient for ensuring secure access to your user's configuration data.

Security Mechanism

The security mechanism built into this process has multiple layers of protection that ensure the safety of the data. Details about the implementation of the protection are not disclosed to maintain maximum security.

Activity Notifications

If there are attempts to unauthorized access to the QR code, the administrator will receive corresponding notifications in the WHMCS activity log. This ensures full control and visibility of any attempts to access the QR code.

Important: It's essential to react to these notifications in the activity log and take appropriate security measures.

Notification Levels

- **High level of danger:** Notifications in the form of "Someone is trying to get a QR code, but the verification words are wrong. [additional data follows]". This indicates an attempt to access the QR code using incorrect verification parameters.
- **Low level of danger:** Notifications in the form of "It looks like someone is trying to get a QR code. [additional data follows]". This indicates an attempt to access, but without any attempt to use verification parameters.

Reacting to Notifications

It's necessary to take appropriate security measures when receiving high-level danger notifications. Upon receiving low-level danger notifications, pay attention, but it's not critical. In any case, you will always be aware of attempts to access the QR code, and you will have the IP address of the device making such requests.

Conclusion

Using this mechanism ensures the safety and control of access to a user's configuration data via QR code.